

概述

Ro8-D Dante

特征

**规格**
**一般规格**


	44.1kHz +4.1667%, +0.1%, -0.1%, -4.0%	± 200ppm
	48kHz +4.1667%, +0.1%, -0.1%, -4.0%	± 200ppm
	88.2kHz +4.1667%, +0.1%, -0.1%, -4.0%	± 200ppm
	96kHz +4.1667%, +0.1%, -0.1%, -4.0%	± 200ppm
	3ms INPUT OUTPUT <sup>*1</sup> , Dante CL5, Dante 0.25ms Fs=48kHz	
	+0.5, -1.5dB 20Hz-20kHz, +4dBu output @1kHz, INPUT OUTPUT <sup>*1</sup> , Fs= 44.1kHz, 48kHz +0.5, -1.5dB 20Hz-40kHz, +4dBu output @1kHz, INPUT OUTPUT <sup>*1</sup> , Fs= 88.2kHz, 96kHz	
<sup>*2</sup>	0.05% 20Hz-20kHz@+4dBu 600», Fs= 44.1kHz, 48kHz 0.05% 20Hz-40kHz@+4dBu 600», Fs= 88.2kHz, 96kHz INPUT OUTPUT <sup>*1</sup> , =	
<sup>*3</sup>	-128dBu typ. = -88dBu ST master	
	112dB DA 108dB typ. INPUT OUTPUT <sup>*1</sup> =	
<b>@1kHz</b>	-100dB <sup>*4</sup> INPUT/OUTPUT =	
<b>xHxD</b>	480mm x 44mm x 359mm (18.9" x 1.7" x 14.13")	
	4.4kg (9.7lbs)	
	35W	
	/ 120V 60Hz 100V 50/60Hz 110-240V 50/60Hz 220V 60Hz 110-240V 50/60Hz	
	0 - 40°C -20 - 60°C	

<sup>\*1</sup> INPUT OUTPUT Ri8-D INPUT Ro8-D OUTPUT

<sup>\*2</sup> 18dB/ @80kHz

<sup>\*3</sup> & A

<sup>\*4</sup> 30dB/ @22kHz

**模拟输出特性**




外可

**建筑 and 工程规格**

---

Yamaha Ro8-D	8	1U	Dante		R Remote
	R			480 (W) x 44 (H) x 359 (D) mm	4.4 kg

\*  
\*

<http://www.yamaha.com.cn/pa/>